# MP 800 Turbo









### **SALES DESCRIPTION**

Ideal for blending soups and puréeing fruit and vegetables. Special institutional catering model intended for intensive use

### **TECHNICAL DESCRIPTION**

MP 800 Turbo Power Mixer. 120V/60/1. Power: 1.6 HP/ 1000 W. Speed: 12000 rpm. 100% stainless-steel blades, bell and shaft (total length: 29"). "Easy Plug" system featuring detachable power cord


### TECHNICAL CHARACTERISTICS **Effective output** 1.6 HP/ 1000 W 120V/60/1 Electrical data 8.4 amps – plug supplied Speed 12000 rpm Recyclability 95% 19 lb Net weight MP 800 Turbo Reference



Pan capacity

up to 300 qt

Specially designed for intensive use in commercial/institutional catering



### **CHARACTERISTICS AND BENEFITS**

### MOTOR UNIT

- Power 1.6 HP/ 1000 W
- Stainless-steel motor unit with air vents in the top section to ensure watertightness
- Ridge on motor housing serves as a rest and pivot on the pan rim for greater user comfort
- Speed 12000 rpm
- New patented "Easy Plug" system making it easier to replace the power cord during after-sales servicing
- Cord winding system for tidy storage and optimum lifespan

### **SHAFT AND BELL**

- 100% stainless-steel blades, bell and shaft (total length:
- Foot with detachable bell and blades (patented system) exclusive to Robot Coupe)
- Watertight bell design for optimum lifespan

### STANDARD ATTACHMENTS

- Wall-mounted power Mixer holder
- Tool for attaching and detaching the blades

### **STANDARDS**

ETL electrical and sanitation Listed/cETL (Canada)

Specification sheet

MP 800 Turbo

www.robotcoupeusa.com

info@robotcoupeusa.com

Update: September 2014



# MP 800 Turbo

### F

## **OPTIONAL ATTACHMENTS**

- 3 adjustable stainless-steel pan supports:
  - Ref. 27363 for pans with a diameter of 13» to 26»
  - Ref. 27364 for pans with a diameter of 20» to 39»
  - Ref. 27365 for pans with a diameter of 33» to 51»
- 1 universal pan support:
  - Ref. 27354 screws on to pan rim (fits any size pan diameter)





# DRAWINGS & DIMENSIONS 120V/60/1 – power cord and plug supplied 7 4/9 8 3/9 8 3/9